PULS does it again: practical, versatile and reliable like the SilverLine – yet small like no other.







# MiniLine ML30.100 with DC 24-28V / 30W

- Mounted and connected in record time, no tools required
- World-wide approvals (UL, EN, CSA, CB Scheme) for industry and office/ home
- Tiny: WxHxD = 45 x 75 x 91mm
- NEC Class 2 Power Supply and Hazardous Location Class I Div. 2 (UL 1604)

- Output voltage adjustable to DC 28V
- 100-240V Wide Range Input (AC 85...264V permitted)
- PULS Overload Design™ (no switch off at overload but up to 1.5 times nominal current)

PULS GmbH, Arabellastrasse 15, D-81925 Munich Tel. +49.(0)89.9278-244, Fax: +49.(0)89.9278-299 sales@puls-power.com, http://www.puls-power.com

## Mini is more.



### Technical Data ML30.100



♦ Input	
Input voltage	AC100-240V (Wide Range), 4763Hz Admiss. limits: AC 85264V (DC 85375V)
Input current	<0.6A (@ AC 100V, 30W P <sub>out</sub> ) <0.35A (@ AC 196V, 30W P <sub>out</sub> )
External Fusing	Not required, unit provides internal fuse (T3AH, not accessible)
Transient immunity	Transient resistance acc. to VDE 0160 / W2 (750V / 1.3ms), over entire load range
Hold-up time (see diagram below)	>190ms bei AC 230V, 24V / 1.3A >107ms @ AC 196V, 24V / 1.3A >19ms @ AC 100V, 24V / 1.3A

#### • Efficiency, Reliability

typ. 87.5% (AC 230V, 24V / 1.3A)	
(see also diagram below)	
typ. 4.5W (AC 230V, 24V / 1.3A)	
ca. 650.000h acc. to Siemensnorm SN 29500 (24V/1.3A, AC 230V, T <sub>amb</sub> = +40°C)	

Prior to shipment, every unit undergoes the following tests in order to isolate any defective units which might suffer an early failure:

- Run-in / burn-in (Full load, T<sub>amb</sub> = +60°C, on/off cycle)
- Functional test (100%)

#### Construction, Mechanics, Installation

Robust plastic housing (US Patent No. D442, 9235), fine ventilation grid on three housing sides to keep out small parts (e.g. screws), IP20

Dimensions and weight

• BxHxT	45mm x 75mm x 91mm (+ DIN Rail) Depth incl. terminals: 98mm (+ DIN Rail)	
• Weight	230g	
Mounting orientation	🗊 , 💮 or 🏠 (cf. 'Output')	
Ventilation/Cooling <ul> <li>Free space f. cooling</li> </ul>	Normal convection, no fan required recom'd.: 25mm on sides with ventilation grid	
, , , ,	onto the DIN-Rail (TS35/7,5 or TS35/15). y on the rail; no tools required even to remove	
Connection	by Spring Clamp terminals; uniformly firm hold, vibration-resistant and maintenance-free: 2 terminals per output	
<u> </u>		

Connector size range

٠	flexible cable	0.3-2.5mm <sup>2</sup> (28-12 AWG)
٠	solid cable	0.3-4mm <sup>2</sup> (28-12 AWG)
		Ferrules admissible
٠	Wire strip length	6mm (0.24in) recommended

🔶 Output	
Output voltage <ul> <li>preset</li> </ul>	DC 24-28V, adj. by front panel potentiometer 24.5V ±0.5%
Voltage regulation	stat. 0.5% V <sub>out</sub> , dyn. ±2% V <sub>out</sub> overall
Ripple/Noise	<50mV <sub>PP</sub> (20MHz bandw., 50 $\Omega$ –measurem.)
Overvoltage prot. (OVP	)<40V
Output noise suppression	EMI values below EN 61000-6-3, even when us- ing long (>2m), unscreened output cables
Rated continuous loading	up to 1.3A (convection cooling) depending on built-in orientation, V <sub>in</sub> and T <sub>amb</sub> ; for details see derating diagram below
Overload behaviour	PULS Overload Design <sup>™</sup> : No switch-off at overload/short-circuit, instead: up to 1.5 · I <sub>rated.</sub> So you need no oversizing to start awkward loads.
Overload behaviour Protection	overload/short-circuit, instead: up to 1.5 · I <sub>rated.</sub> So you need no oversizing to start awkward
	overload/short-circuit, instead: up to 1.5 · I <sub>rated.</sub> So you need no oversizing to start awkward loads. Unit is protected against (also permanent)
Protection	overload/short-circuit, instead: up to 1.5 · I <sub>rated.</sub> So you need no oversizing to start awkward loads. Unit is protected against (also permanent) short-circuit, overload and open-circuit depending on built-in orientation;
Protection Derating	overload/short-circuit, instead: up to 1.5 · I <sub>rated.</sub> So you need no oversizing to start awkward loads. Unit is protected against (also permanent) short-circuit, overload and open-circuit depending on built-in orientation; see diagram below

#### Environmental Data, EMC, Safety

Ambient tem	perature range	Impactured	25mm	holow	unit)
Amblent tem	perature range	(ineasureu	23111111	DEIOW	unity

Amplent temperature range (measured 25mm below unit)		
<ul> <li>storage, transport</li> </ul>	-25°C +85°C	
<ul> <li>operation</li> </ul>	-10°C +70°C (for derating see diagram below)	
Humidity	max. 95% (without condensation)	
Electromagnetic emissions (EME)	EN 61000-6-3 (includes EN 61000-6-4) Class B (EN 55011, EN 55022) incl. output noise suppression	
Electromagnetic immunity (EMI)	EN 61000-6-2 (includes EN 61000-6-1)	
Safe low voltage: Prot. class/degree:	SELV (EN60950, VDE0100/T.410), PELV (EN50178) Class I (EN60950) / IP20 (EN60529)	

The PSU complies with all major **safety approvals** for EU (EN 60 950, EN 60204-1, EN 50178), USA (UL 60950, E137006, UL508 LISTED, E198865), Canada (CAN/CSA-C22.2 No 60950 [CUR], CAN/CSA-C22.2 No. 14 [CUL]), CB Scheme (IEC 60950). NEC Class 2 Power Supply and Hazardous Location Class I Div. 2 (UL 1604)

Design details – for your advantage:

- All terminals are easy to reach as mounted on the front panel.
- Input and output are strictly apart from each other (input below, output above) and so cannot be mixed up
- Mounting and connection do not require any screwdriver
- $\rightarrow$  Easy, quick, durable and reliable installation

#### ♦ Diagrams



Product information (ML30e100 / 040629), Rev.: 29. June 2004

Unless otherwise stated, specifications are valid for AC 230V input voltage, +25°C ambient temperature, and 5 min. run-in time. They are subject to change without prior notice.. PULS GmbH, Arabellastr. 15, D-81925 München  $\blacklozenge$  Tel: +49.(0)89.9278-244, Fax: +49.(0)89.9278-299, E-Mail: sales@puls-power.com  $\blacklozenge$  www.puls-power.com